








Reflective photoelectric components

Encapsulation form	model	Receiver type	Best response position (mm)	Receiver bright current		LED direct voltage		Rising and drop-out time μ s	Internal transistor component model	operating temperature range °C
				least value (mA)	Test condition Angle @I _r (mA)	crest value (V)	Test conditions (mW/cm ²)			
	HOA0149-001	dynatron	5	1.00	40	1.6	20	15	SEP8505 SDP8405	-40 to 85
	HOA0708-001	dynatron	3.8	0.20	40	1.6	20	15	SEP8505	-40 to 85
	HOA0708-011*	dynatron	3.8	0.20	40	1.6	20	15	SDP8405	
	HOA0709-001	Darlington	3.8	1.00	40	1.6	20	75	SDP8105	
	HOA0709-011*	Darlington	3.8	1.00	40	1.6	20	75		
	HLC1395-001	dynatron	1	0.30	10	1.6	20	15		-40 to 85
	HLC1395-002	dynatron	1	0.60	10	1.6	20	15		
	HOA1397-001	dynatron	1.3	0.20	20	1.6	20	15	SEP8507	-40 to 85
	HOA1397-002	dynatron	1.3	0.70	20	1.6	20	15	SDP8407	
	HOA1397-031	Darlington	1.3	2.00	20	1.6	20	75		
	HOA1397-032	Darlington	1.3	7.00	20		20	75		
	HOA1404-001	dynatron	5	0.20	30	1.6	20	15	SE1450	-55 to 100
	HOA1404-002	Darlington transistor	5	0.80	30	1.6	20	15	SD1440	
	HOA1404-003		5	2.00	30	1.6	20	75	SD1410	
	HOA1405-001*	dynatron	5	0.20	30	1.6	20	15	SEP8505	-40 to 85
	HOA1405-002*	dynatron	5	0.80	30	1.6	20	15	SDP8405	
	HOA2498-001	dynatron	6.4	0.04	30	1.6	20	15	SE1450	-55 to 100
	HOA2498-002	dynatron	6.4	0.16	30	1.6	20	15	SD1440	
	HOA2498-003	Darlington	6.4	2.00	30	1.6	20	75	SD1410	

* The sensor uses a dustproof filter that allows infrared light to pass through the transmit-receive surface.

深圳市杰晟兴电子有限公司 JM Components Limited

地址: 深圳市福田区中航路7号鼎诚国际大厦南座2007室
 手机: 13662266995 马少良 电话: 0755-83951311
 官网: cn-sensor.com

邮编: 518031
 传真: 0755-83952401
 电邮: jackson@jmcomponents.com